

Callvoip configuratie-handleiding voor Cisco Linksys SPA IP Phones

v030222MT

In deze handleiding kunt u lezen hoe u uw Linksys SPA of Cisco SPA IP Phone instelt voor een VoIP-account van de Callvoip telefooncentrale.

1. Maak een Callvoip toestelaccount aan

Voordat u de telefoon kunt instellen maakt u op de Callvoip centrale aan:

- een gebruiker
- een toestel-account → hier vindt u ook de SIP-username en password

Voor meer informatie, raadpleeg de Callvoip supportpagina.

2. Sluit de IP Telefoon aan

Aan de achterkant van de IP Telefoon zitten één of twee internet-aansluitingen. Sluit op de WAN- of SW-poort* (en NIET op de PC Poort) een netwerkkabel op aan en sluit de kabel aan de andere zijde aan op uw netwerk/router zodat de IP telefoon met internet is verbonden.

* Sommige modellen (o.a. SPA9x2, SPA504) hebben naast de poort voor de internetaansluiting (Switch / WAN) Powe een extra poort voor het aansluiten van een PC (PC Poort). Zie afbeelding.

Auxiliary Port (Use only with SPA500S) Upper Slots Lower Slots Port Switch / WAN (Network) Por Cable Slot Handset Port

3. Vraag het IP-adres van de telefoon op:

Druk op de toets met het blaadje (instellingen) + 9 om het IP-adres op te vragen.

4. Log in op de configuratiepagina van de SPA IP-telefoon

- Ga naar internet en toets het IP-adres met de puntjes in de browser-adresbalk in.
- Druk rechtsboven in eerst op [admin login] en vervolgens op [advanced]. Het aantal tabbladen wordt uitgebreid. Volg de instructies om de instellingen te doen.

5. de SPA IP Phone configureren

Om de SPA IP Phone in te stellen gaat nu naar tabblad [Ext1]. Deze pagina is in een aantal compartimenten ingedeeld. Op de volgende pagina ziet u aangegeven bij welke velden wij welke aanpassing aanraden om uw Simmpl-account te registreren. Klik na het invullen van de velden op [Submit all changes] om de wijzigingen vast te leggen. De telefoon wordt geherstart.

> ING BANK 5041280 IBAN NL66INGB0005041280 BIC INGBNL2A KVK 02066541 BTW NL1041.63.252.B01

Koldingweg 19-1 9723 HL Groningen

Postbus 5236 9700 GE Groningen

- T (050) 820 00 00
- F (050) 820 00 08
- E aanvraag@callvoip.nl
- W www.callvoip.nl

6. De IP telefoon aanpassen aan uw eigen wensen en voorkeuren

Op tabblad [Phone] kunt u nog een paar zaken aanpassen om het display van de telefoon (naam van de telefoon, naam van de lijn) aan uw wensen aan te passen. Ook kunt u daar het voicemailbox-nummer instellen. Met de speciale [voicemail-button] op de telefoon kunt u dan in één kaar naar uw voicemailbox bellen.

Op tabblad [User] tenslotte kunt u nog het formaat van tijd en datum invullen. Geluid van de telefoon te zacht? Een paar tips.

- gebruik de laatste firmware, Linksys heeft hier wat verbetering in aangebracht
- zet onderaan tab [User] de [handset input gain] op [6]

Tabblad Info

U start altijd op tabblad info. Hier vindt u informatie over o.a. de firmwareversie, het IP-adres en de status van de accounts. Deze status dient na configuratie [**Registered**] te zijn.

cisco SPA504	ess 4G Configuration Util	lity						User Login basic advanced
Voice	Call History	Personal Direc	ectory Attendant Console	Status		[-	
Info	System SIP	Provisioning	Regional Phone	Liser A	ttendant Console		Op	de Ext-tabbladen kunt u
544	540 E42	Evid	rtogional rhono				ind	lividuele VoIP-accounts
EALT		EM 4					ins	tellen
System Information								
	Connection Type:	DHCP CEDC (OFFICIALCO			Current IP:	192.168.178.23		
	Host Name.	3EP049EF370E132			Current Onterine	1012-00X		
	Drimany DNS:	400 469 479 054			current Gateway.	192.100.170.254		
	Primary DNS.	192.100.170.254					Hie	er vindt u.o.a. het model en
	Secondary DNS.							
Product Information			•				de	firmwareversie.
	Product Name:	SPA504G			Serial Number:	CBT15510DKC		
	Software Version:	7.4.8a			Hardware Version:	1.0.3		
	MAC Address:	649EF376E152			Client Certificate:	Installed		
	Customization:	Open			Licenses:	None		
Phone Status								
	Current Time:	6/8/2014 02:45:26			Elapsed Time:	1 day and 19:42:14	[
	Broadcast Pkts Sent:	6			Broadcast Bytes Sent:	880	_	Hier vindt u de status van
	Broadcast Pkts Recv:	163125			Broadcast Bytes Recv:	9815192		mer vinut u de status van
	Broadcast Pkts Dropped:	0			Broadcast Bytes Dropped:	0	_	Ext 1 ofwel de eerste
	RTP Packets Sent:	0			RIP Bytes Sent:	0		accountrositio in dozo
	RTP Packets Recv:	0			RTP Bytes Recv:	0	_	
	SIP Messages Sent:	13320			SIP Bytes Sent	1017073		teleroon. Arnankelijk van
	SIP Messages Recv:	2000			SIP Bytes Recv:	1214513		het model zijn er
	External IP:	100M Eul Dupley			Operational VEAN ID:	Unit Down		moordoro II kunt to in
	SW Port:	room run Duplex			PC Port:	Link Down		meerdere. O kunt zo m
Ext 1 Status								één oogopslag zien wat de
	Registration State:	Registered			Last Registration At:	6/8/2014 02:43:19	\rightarrow	status van deze accounts
	Next Registration In:	12 s			Message Waiting:	No		
	Mapped SIP Port:							IS.
Ext 2 Status								
			Undo All Changes	Submit All Changes				
© 2009 Cisco Systems, Inc.	. All Rights Reserved.	ini Ili			날빤했?!! 김			SPA504G IP Phone

Tabblad SIP

Voordat u het account instelt, is het van belang om te checken of onderstaande waarde goed staat.

cisco SPA504G Configuration	Utility		Ust	<u>er Loqin</u> <u>Dasic</u> advanced
Voice Call History	Personal D	rectory Attendant Console Status		
Info Sustam	Provisioning	Pagional Dhone I Hear Attendant Concole		
Ext 1 Ext 2 Ext 3	Ext 4			
				*
IP Parameters			-	
Max Forward: Max Auth:	70	Max Redirecti	n: 5	
SIP Server Name:	\$VERSION	SiP dell'Agent Nar	e:	
SIP Accept Language:		DTMF Relay MIME Typ	e: application/dtmf-relay	
Hook Flash MIME Type:	application/hook-flash	Remove Last R	g: no 🔻	
Use Compact Header:	no 🔻	Escape Display Nar	e: no 🔻	
SIP-B Enable:	no 🔻	Talk Packa	e: no 🔻	
Hold Package:	no 🔻	Conference Packa	e: no 🔻	
Notify Conference:	no 🔻	RFC 2543 Call Ho	d: yes ▼	
Random REG CID On Reboot:	5060	Mark All AVT Packe	s: yes V	
CTI Fnable:	no T	SPICP FOR M	r: PAID-RPID-FROM V	
SRTP Method:	x-sipura V	Hold Target Before REFE	R: no V	
Dialog SDP Enable:	no 🔻			
imer Valuer (rec)				
siP T1:	1	SP	2: 4	
SIP T4:	5	SP Timer	B: 16	
SIP Timer F:	16	SIP Timer	H: 16	
SIP Timer D:	16	SIP Time	J: 16	
INVITE Expires:	240	RelNVITE Expin	s: 30	
Reg Min Expires:	30	Reg Max Expin	d: 1200	
Reg Retry Random Delav:		Reg Retry Long Random Del	y:	
Reg Retry Intvi Cap:		Sub Min Expin	s: 10	-
Reg Retry Random Delay:		Rea Retry Long Paorian Del	y:	
Reg Retry Intvi Cap:		Sub Min Expire	s: 10	
Sub Max Expires:	7200	Sub Retry In	vt 10	
nse Status Code Handling				
SIT1 RSC:		SIT2 R5	C:	
SIT3 RSC:		SIT4 RS	C:	
Try Backup RSC:		Retry Reg R	C:	
ameters				Het is nood:
RTP Port Min:	16384	RTP Port M	x: 16538	RTP Packe
RTP Packet Size.	0	No UDP Checksu	m: no T	op 0.020 .
Symmetric RTP:	no 🔻	Stats In B	E: no V	[Not Accent
dead Tomas				
AVT Dynamic Payload:	101	INFOREQ Dynamic Paylo	d:	Let op: af f
G726r16 Dynamic Payload:	98	G726r24 Dynamic Paylo	d: 97	waarde op (
G726r32 Dynamic Payload:	2	G726r40 Dynamic Paylo	d: 96	
G729b Dynamic Payload:	99	EncapRTP Dynamic Paylo	d: 112	
RTP-Start-Loopback Dynamic Payload:	113	RTP-Start-Loopback Cod	c: G711a ▼	
AVT Codec Name:	telephone-event	G711u Codec Nar	e: PCMU	
G711a Codec Name: G726r24 Codec Name:	G726-24	G726/16 Codec Nar	e: G726-16	
G726r40 Codec Name:	G726-40	G729a Codec Nar	e: G729a	
G729b Codec Name:	G729ab	G722 Codec Nar	e: G722	
EncapRTP Codec Name:	encaprtp			
upport Parameters				
Handle VIA received:	no 🔻	Handle VIA rpo	t no 🔻	
Insert VIA received:	no 🔻	Insert VIA rpo	t no 🔻	
Substitute VIA Addr:	no 🔻	Send Resp To Src Po	t no 🔻	
STUN Enable:	no 🔻	STUN Test Enabl	no 🔻	
STUN Server:		EXT		
EXT RTP Port Min:	L	NAT Keep Alive Int	t 15	
Key System Parameters				
Linksys Key System:	no 🔻	Multicast Addres	: 224.168.168.168:6061	
	Ves T	Key System IP Addres	C	
Key System Auto Discovery:	900			
Key System Auto Discovery: Force LAN Codec:	none V			
Key System Auto Discovery: Force LAN Codec:	none T	Undo All Changes Submit All Changes		
Key System Auto Discovery: Force LAN Codec:	none T	Undo All Changes Submit All Changes		

Instellen van uw Callvoip toestel-account

Om uw Simmpl account in te stellen, ga naar tabblad Ext 1 of een volgend tabblad en vul die als volgt in:

sco SPA504G Configuration	Jtility		<u>User Login</u> basic
Voice Call History	Personal Directory Attendant Console Statu		
Info System SIP	Provisioning Regional Phone	User Attendant Console	
Ext1 Ext2 Ext3	Ext4		
re Line Appearance			
Share Ext:	private T	Shared User ID:	
Subscription Expires:	3600	Restrict MWI:	no 🔻
Monitor User ID:			
Settings			
NAT Mapping Enable:	no 🔻	NAT Keep Alive Enable:	yes 🔻
NAT Keep Alive Msg:	SSP	NAT Keep Alive Dest:	SPROXY
vork Settings			
SIP TOS/DiffServ Value:	0x68	SIP CoS Value:	3 🔻
RTP TOS/DiffServ Value:	0xb8	RTP CoS Value:	6 🔻
Network Jitter Level:	high 🔻	Jitter Buffer Adjustment:	up and down 🔻
Settings			
SIP Transport:	UDP V	SIP Port:	5060
SIP 100REL Enable:		EXT SIP Port:	
Auth Resync-Reboot:	yes 🔻	SIP Proxy-Require:	
SIP Remote-Party-ID:	no 🔻	Referor Bye Delay:	4
Refer-To Target Contact:	no T	Referee Bye Delay:	0
SIP Debug Option:	none 🔻	Refer Target Bye Delay:	0
Sticky 183:	no T	Auth INVITE:	no T
Ntfy Refer On 1xx-To-Inv:	yes 🔻	Use Anonymous With RPID:	yes T
Set G729 annexb:	none	Voice Quality Report Address:	
eature Settings			
Blind Attn-Xfer Enable:	no 🔻	MOH Server:	
Message Waiting:	no V	Auth Page:	no 🔻
Default Ring:	1 •	Auth Page Realm:	
Conference Bridge URL:		Auth Page Password:	
Mailbox ID:	1233	Voice Mail Server:	
Voice Mail Subscribe Interval:	86400	State Agent:	
CFWD Notify Serv:	no 🔻	CFWD Notifier:	
User ID with Domain:	no V	Auto Ans Page On Active Call:	yes 🔻
and Registration			
Proxy:	pbx.callvoip.nl		
Outbound Proxy:	pbx.callvoip.nl		
Use Outbound Proxy:	yes V	Use OB Proxy In Dialog:	yes 🔻
Register:	yes 🔻	Make Call Without Reg:	no 🔻
Register Expires:	180	Ans Call Without Reg:	no 🔻
Use DNS SRV:	yes V	DNS SRV Auto Prefix:	no T
Proxy Fallback Intvi:	3600	Proxy Redundancy Method:	Based on SRV Port V
criber Information			
Display Name:	Callvoip - 220	User ID:	pvlmqqaw9hnj
Password:	*****	Use Auth ID:	yes 🔻
Auth ID:	pvlmqqaw9hnj		
Mini Certificate:			
SRTP Private Key:			
o Configuration			
Preferred Codec:	G711a 🔻	Use Pref Codec Only:	yes 🔻
Second Preferred Codec:	G711u 🔻	Third Preferred Codec:	Unspecified T
G729a Enable:	yes ▼	G722 Enable:	yes 🔻
G726-16 Enable:	yes 🔻	G726-24 Enable:	yes 🔻
G726-32 Enable:	yes 🔻	G726-40 Enable:	yes 🔻
Release Unused Codec:	yes 🔻	DTMF Process AVT:	yes 🔻
Silence Supp Enable:	no 🔻	DTMF Tx Method:	Auto 🔻
DTMF Tx Volume for AVT Packet:	0	Use Remote Pref Codec:	no 🔻
	Default 🔻		
Codec Negotiation:			
Codec Negotiation:			
Codec Negolialion: Plan Dial Plan:	(*xx[[3469]11]0[00][2-9]xxxxxxxxxxxxxxxxxxxxxxxxxxxxxxxxxxxx		
Codec Negotiation: Plan Dial Plan: Caller D Nap:	(*xe([3469]110(00[[2-9]xxxxxxx;1xxxe[[2-9]xxxxxxxx50]xxxxxxxxxxxx)		
Codec Negotiation: Man Dial Plan: Cater D Map: Enable P Dialing:	(*xx[3469]11(000]2-9]xxxxxx(1xxx(2-9)xxxxxx50)xxxxxxxxxxx) yes •	Emergency Number:	

Indien u problemen ervaart met het gebruik van *-codes, kunt u de code in veld DialPlan aanpassen naar:

Hieronder vindt u een aantal tabbladen waar u de telefoon verder aan uw wensen kunt aanpassen. Deze zijn niet noodzakelijk om te kunnen bellen en gebeld te kunnen worden.

Tabblad Regional

Scroll helemaal naar beneden; linksonder vindt u de instellingen voor de tijdzone.

cisco SPA	^{iusiness} 504G Con	figuration	Utility						<u>User Loqin</u>	basic advanced
Voice		Call History	Personal Di	rectory	Attendant Console Status					
Info	System	SIP	Provisioning	Regional	Phone	User	Attendant Console			
Ext 1	Ext 2	Ext 3	Ext 4							
		Paging Lode:	.ao]			Call Park Code:	138	_	*
		Call Pickup Code:	*36]			Call UnPark Code:	*39		
	Group	p Call Pickup Code:	*37]			Media Loopback Code:	*03		
	Referra	al Services Codes:								
	Feature Dia	al Services Codes:								
Vertical Service An	nouncement Code	es								
Vortabar borrido Ali	Service A	nnc Base Number:]						
	Service Anno	c Extension Codes:		-						
Outbound Call Code	c Selection Code:	S refer G711u Code:	*017110	1			Force G711u Code:	*027110		
	P	refer G711a Code:	*017111]			Force G711a Code:	*027111	-	
	F1	Prefer G722 Code:	*01722]			Enroe G722 Code:	*02722		
	Dre	fer G728r18 Code:	*0172616]			Force G726r16 Code:	*0272616	-	
	Bra	for G726r24 Code:	*0172624]]			Force 0720r70 Code:	10272624	-	
	Pre	fer G726r32 Code:	*0172622]			Force G726r32 Code:	*0272632	-	
	Dre	fer G726r40 Code:	*0172640]			Force G726r40 Code:	*0272640	_	
		refer 0729a Code:	*01729]			Force 0720a Code:	102720	-	
	F	relet Grzsa coue.	01725]			10106 07258 0006.	02725		
Miscellaneous										
	Set Lo	ocal Date (mm/dd):					Set Local Time (HH/mm):			
		Time Zone:	GMT+01:00 ▼				Time Offset (HH/mm):			
	Ignore ¹	DHCP Time Offset:	yes 🔻							
	Daylight	t Saving Time Rule:								
	Daylight S	aving Time Enable:	yes 🔻				DTMF Playback Level:	-16		
	DTM	F Playback Length:	.1]			Inband DTMF Boost:	12dB 🔻		
	Diction	nary Server Script:								
	Li	anguage Selection:]			Default Character Encoding:	ISO-8859-1 V		
				Undo All Cha	anges Submit All Ch	hanges				
© 2009 Cisco System	is, Inc. All Rights R	teserved.								SPA504G IP Phone

Tabblad Phone

Hier kunt u bepalen wat u in het display van de telefoon ziet en welke accounts bij welke displayknoppen horen.

cisco SPA50	^{ness})4G Configurat	on Utility				Use	<u>er Login</u> <u>basic</u> advanced	
Voice	Call Histo	ry Persona	I Directory Attenda	int Console Status				
Info	System	IP Provisioning	Regional	Phone Us	ser Altendant Console			
Ext 1	Ext 2 E	t3 Ext4					Bepaal de na	am van het
Conoral							toestel, deze	is zichtbaar in het
General	Station M	ame: Callvopi 500			Station Display Name:	Callvoip 500 - Milan	display van d	le telefoon
	Voice Mail Nu	nber: *969000			Text Logo:			
	BMP Picture Download	URL:					Stel hier het	voicemailnummer
	Select	.ogo: Default 🔻			Select Background Picture.	None V	in om met ée	én druk op de
	Softkey Labels	Font: Auto 🔻			Screen Saver Enable:	no 🔻	message-but	ton gelijk de
	Screen Saver	Wait: 300			Screen Saver Icon:	Background Picture 🔻	voicemail te	kunnen
Line Key 1							beluisteren.	
	Exter	sion: 1 🔻			Short Name:	Callvoip 500		
	Share Call Appear	ince: private T						
	Extended Fun	tion:						
Line Key 2								i [Extension]
	Exter	sion: 1 🔻			Short Name:	SUSER		
	Share Call Appear	ince: private v					30	count (nummer)
	Extended Fun	stion:						e knop gebruikt.
Line Key 3								
	Exter	sion: 2 🔻			Short Name:	TijdhofConsulting		
	Share Call Appear	ince: private 🔻					В] [shortname]
	Extended Fun	tion:					St	eit u in noe de lijn
Line Key 4								lefault: SImmpl
	Exter	sion: 2 🔻			Short Name:	SUSER		[P username).
	Share Call Appear	ince: private 🔻					L	et op: u heeft
	Extended Fun	tion:					m	aar weinig ruimte
Miscellaneous Line Key	v Settings						in	uw display.
			Undo All Changes	Submit All Change	s			
© 2009 Cisco Systems, In	nc. All Rights Reserved.				أشريح ومستحسيل		SPA504G IP Phone	

Tabblad User

Hier kunt u diverse zaken instellen die te maken hebben met persoonlijke gebruiksvoorkeuren, zoals functies die aan of uitstaan, speeddialtoetsen, audiovolume, LCD contrast, etc.

Voice Info Exit 1	Call History System SIP Ext 2 Ext 3 Ctrvd No Ans Uest Speed Dial 2: Speed Dial 4: Speed Dial 6: Spee	Personal D	Nirectory Attendant Console Status Regional Phone User Attendant Console Ctwd No Ans Lelsy: Ctwd No Ans Lelsy: Ctwd No Ans Lelsy:	20	
Info Exit 1	System SIP Ext 2 Ext 3 Utwo I No Ans Dest Speed Dial 2: Speed Dial 4: Speed Dial 6: Speed Dial 6: Speed Dial 6:	Provisioning Ext 4	Regional Phone User Attendant Console CTwd No Ans Usey:	20	
Ext 1	Ext 2 Ext 3 Ctwd No Ans Dest Speed Dial 2: Speed Dial 4: Speed Dial 6: Speed Dial 6:	Ext 4	Ctwd No Ans Delay:	20	
beed Dial	Speed Dial 2: Speed Dial 4: Speed Dial 6: Speed Dial 6: Speed Dial 6:				
ipplementary Service	Speed Dial 2: Speed Dial 4: Speed Dial 6: Speed Dial 6: Speed Dial 6:		Creat Disto		
ipplementary Service	Speed Dial 4: Speed Dial 6: Speed Dial 8:		Speed Dial 3:		
ipplementary Service	Speed Dial 6: Speed Dial 8:		Speed Dial 5:		
ipplementary Service	Speed Dial 8:		Speed Dial 7:		
ipplementary Service			Speed Dial 9:		
	ces				
	CW Setting:	yes 🔻	Block CID Setting:	yes 🔻	
	Block ANC Setting:	no 🔻	DND Setting:	yes 🔻	
	Secure Call Setting:	no 🔻	Dial Assistance:	no 🔻	
	Auto Answer Page:	yes 🔻	Preferred Audio Device:	Speaker 🔻	
	Send Audio To Speaker:	no 🔻	Time Format:	12hr 🔻	
	Date Format	month/day 🔻	Miss Call Shortcut:	yes 🔻	
	Miss Call Banner:	yes 🔻	Accept Media Loopback Request:	automatic 🔻	
	Media Loopback Mode:	source 🔻	Media Loopback Type:	media 🔻	
	Text Message:	yes 🔻	Text Message From 3rd Party:	no 🔻	
	Alert Tone Off:	no 🔻	Log Missed Calls for EXT 1:	yes 🔻	
	Log Missed Calls for EXT 2:	yes 🔻	Log Missed Calls for EXT 3:	yes 🔻	
	Log Missed Calls for EXT 4:	yes 🔻			
dio Volume			_		
	Ringer Volume:	8	Speaker Volume:	8	
	Handset Volume:	10	Headset Volume:	10	
	Deep Bass:	Default 🔻			
D					
	LCD Contract	8	Back Light Timer:	10 s 🔻	
	Lob Contrast.				
100 Cisco Systema J	Lop contrast.		Undo All Changes Submit All Changes		

Checking DNS Error

IIII Small Busines	ss G Configu	ration Ut	ility				<u>User Login</u>	<u>basic</u> advan	ed
	ooninga								
Voice	Call	History	Persona	al Directory A	ttendant Console Sta	tus			
Info	System	SIP	Provisioning	Regional	Phone	User	Attendant Console		
Ext 1	Ext 2	Ext 3	Ext 4						
PI	hone-UI-user-mode	: no ▼							•
Power Setting									
P	oE Power Required	: Normal	•						
ternet Connection Type									
ternet connection Type	Connection Type	DHCP	•			Use Backup IP:	yes 🔻	Ale	h
								AIS	u u tarf
atic IP Settings	Static IF	p.				NetMask:		toe	stel
	Gateway	:				riotinion.		[ch	-ck
								krij	at k
Ional Network Configur	HostName	e				Domain:		tab	olad
	Primary DNS	()				Secondary DNS:		de	DN
	DNS Server Orde	: Manual	۲		[DNS Query Mode:	Sequential 🔻	Mod	le]
DNS	S Query TTL Ignore	no 🔻				Syslog Server:		[Se	que
	Debug Serve					Debug Level:	0 🔻		
	Layer 2 Logging	: no 🔻				NTP Enable:	yes 🔻		
F	Primary NTP Serve	:			Seco	ndary NTP Server:			
	Enable SSLv3	i no 🔻							
AN Settings									
	Enable VLAN	: no 🔻				Enable CDP:	yes 🔻		
	Enable LLDP-MED	: yes ▼			Netw	vork Startup Delay:	3		
	VLAN IE	: 1			PC Port VLA	AN Highest Priority:	No Limit 🔻		
Enable PC	Port VLAN Tagging	: no 🔻				PC Port VLAN ID:	1		
ventory Settings									
	Asset ID	:							-
			Lindo All	Changes Submi	it All Changes				
			UNU AI	Subini	it Air Changes				

Productafbeeldingen





Link naar website fabrikant:

http://www.cisco.com/c/en/us/support/collaboration-endpoints/small-business-ip-phones/tsd-productssupport-series-home.html

Resetten naar factory defaults:

Druk op de toetst met het blaadje en dan 14 en kies [select]



Bevestig de factory reset; de LEDs van de telefoon gaan knipperen en de telefoon herstart.



Daarna initialiseert hij en komt hij met fabrieksinstellingen terug.





Callvoip Koldingweg 19-1 9723 HL GRONINGEN

T: 050 - 820 00 00 F: 050 - 820 00 08

@: callvoip@callvoip.nl
W: www.callvoip.nl

